

## 5 Through 40VA Transformers

- 12" primary leads, stripped 3/4" and twisted
- AC to AC only
- Class 2 rated
- 50/60 Hz
- Secondary connections have screw terminals

Mount to standard 7/8" knockout (1/2" trade size), which simplifies installation and eliminates the need to inventory transformers with different mounting styles. Mounting foot plate included. If mounting on a 1900 box or 4" square box is required, order cover plate No. 4X748. UL and C-UL Listed.

Uses: Relays, chimes, bells, thermostats, HVAC equipment, and electrical apparatus.

### UNIVERSAL MOUNT COVER PLATE

For mounting transformers Nos. 4X742 through 4X747, on front of any 1900 or 4" square junction box.



No. 4X742



No. 4X743



No. 4X747



No. 4X748

VA Rated	Input Voltage	Output Voltage	Dimensions (In.)			Mr. Model	Item No.	\$ Each	Shpg. Wt.
			W	H	D				
5	120	10	1.97	1.97	2.60	DCT-5-120	4X742		0.7
10	120	16	1.97	1.97	2.60	DCT-10-120	4X743		0.7
20	120	24	1.97	1.97	2.90	DCT-20-120	4X744		0.9
20	240	24	1.97	1.97	2.90	DCT-20-240	4X745		1.0
40	120	24	1.97	1.97	3.30	DCT-40-120	4X746		1.5
40	240	24	1.97	1.97	3.30	DCT-40-240	4X747		1.4
Universal Mount Cover Plate						BR-146-01	4X748		0.3

## 40 Through 75VA Transformers

- Class 2 rated
- AC to AC only

Energy limiting with a wide range of primary voltage inputs and mounting styles to power 24VAC control systems and step down available line voltage. Overload and short circuit protection. Extended secondary short circuits cause primary winding to open, minimizing fire hazards.

Uses: Designed for industrial and HVAC control applications. Can be used as replacement transformers for appliance requiring step down from line voltage to 24VAC.



No. 6WU91



No. 3A358



No. 6WU94



No. 6WU95

VA Rating	Mounting Type	Input Voltage	Output Voltage	Dimensions (In.)			Mr. Model	Item No.	\$ Each	Shpg. Wt.
				W	H	D				
40	Foot	120/208/240	24	2.19	2.75	3.25	90-T40F3	6WU91		1.6
40	Foot Or Plate	120	24	2.44	2.75	3.25	90-T40M1	6WU92		2.1
40	Foot Or Plate	120/208/240	24	2.44	2.75	3.25	90-T40M3	6WU93		2.1
40	Plate	120	24	2.25	2.25	2.50	S84A-410	3A358		1.8
60	Foot	120/208/240	24	3.25	2.62	4.00	90-T60C3	6WU94		2.4
75	Foot	120/208/240	24	3.53	2.62	4.00	90-T75C3	6WU95	✓	2.7

## 96VA Power Transformer

- Dual primary/dual secondary
- UL Recognized (E68100)
- AC to AC only
- 50/60 Hz
- Solder lug termination

For automatic assembly equipment and automatic musical equipment, relays, solenoids, speed changers, door openers, spark plug testers, heating elements, and electronic tubes. Also for small motors, elevators, pumps, fans and blowers, and control valves for fluids and gases, mechanical and electrical signs, signal lamps, and low voltage lighting.



VA Rating	Mounting Type	Input Voltage	Output Voltage	Dimensions (In.)			Mr. Model	Item No.	\$ Each	Shpg. Wt.
				W	H	D				
96	Foot	120/240	24/12	2.81	3.00	3.50	90-T96F2	3T265	✓	4.8