

UL

CSA■

120V AC


60 Hz

A = 163.5mm

B = 47.6mm

C = 38.1mm

D = 152.4mm



(Class P, Indoor and Type 1 Outdoor, HL)

Preheat Ballast (USA/Canada)

UL-Listed for indoor use (outdoor use where applicable) and CSA Certified where applicable. Designed in accordance with ANSI C82.1. The preheat ballast is designed for use with general fluorescent lamps and require the use of a starter. This ballast deliver an open circuit voltage high enough to activate the starter to preheat lamp filaments to a temperature of approximately 1750°F (955.2°C) After a few seconds, the starter opens the filament circuit. This provides an additional power surge to enable an electric arc to strike through the lamp thus igniting the lamp. Lamp current is then limited by the ballast to an operating level proper for the lamp.

Catalog Number	UPE/Pack		Wght ea	EDP No	Nominal Lamp Type		#	mA	Starter
202-B-TC-P■	20/1	C	838g	100188	F40T12ES, FC12T9, F40T12, F40T10, F30T8, F30T12 & F282D	28-40W	1	670	FS-4 1