

RCD Safety Adaptor



**K03-C RCD Adaptor High Speed (15mS) Active
(New piezo actuation technology)
needs resetting after a power loss**

TECHNICAL DATA

Rated Voltage:	230V AC-50Hz
Maximum operating current:	13A Resistive 3A Inductive
Rated Trip Current:	30mA
Maximum load:	3kW
Trip speed:	15mS typical
Electrical latching (Active)	
RCD Contact break:	Double Pole
Tripped indication:	Mechanical flag

This stylishly designed, easy to operate RCD Safety Adaptor conform to BS 7071 and give added protection against electrocution when used with electrical appliances and equipment. They are portable 13 amp adaptors which provide double pole protection from earth leakage current, and simply plug into any standard 13A socket. An essential safety accessory for the tool box, you can always ensure you benefit from RCD protection – especially when operating your portable appliance on unfamiliar circuits.

Ideal applications include; lawnmowers, power tools, irons, kettles, hedgetrimmers and virtually any portable electrical appliance. In the event of a power failure, the no volt drop out feature prevents unexpected start up.

- **Conforms to BS7071**
- **Suitable for use with electrical household appliances and power tools**
- **Easy to operate and test**
- **No wiring**
- **Fits a standard 13 amp BS1363 socket outlet**

K03

